

AD-A095 249

VIRGINIA POLYTECHNIC INST AND STATE UNIV BLACKSBURG
MONITORING AN INPUT-OUTPUT MODEL FOR PRODUCTION. I . THE CONTRO-ETC(U)
DEC 80 D R JENSEN, Y V HUI, P M GHARE DAAG29-78-G-0172
RR-0-6 ARO-15194.7-M NL

UNCLASSIFIED

1 of 1
AD-A
389229



END
DATE
FILMED
3-81
DTIC

AD A095249

18 [ARO] 15194.7-M

(19)

(12)

(C)

MONITORING AN INPUT-OUTPUT MODEL FOR PRODUCTION. I. THE CONTROL CHARTS.

(9)

RESEARCH REPORT NO. Q-6

LEVEL II

(10)

D. R. JENSEN, Y. V. HUI AND P. M. GHARE

(11)

DECEMBER 1980

(14) RR-Q-6

U. S. ARMY RESEARCH OFFICE

DTIC
ELECTE
S FEB 18 1981 D

E

(15)

GRANT NO. DAAG-29-78-G-0172

(12)

VIRGINIA POLYTECHNIC INSTITUTE
AND STATE UNIVERSITY

APPROVED FOR PUBLIC RELEASE;
DISTRIBUTION UNLIMITED

5
2
1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093

THE FINDINGS IN THIS REPORT ARE NOT TO BE
CONSTRUED AS AN OFFICIAL DEPARTMENT OF THE
ARMY POSITION, UNLESS SO DESIGNATED BY OTHER
AUTHORIZED DOCUMENTS.

TABLE OF CONTENTS

ITEM	PAGE
ABSTRACT	1
INTRODUCTION	2
PRELIMINARIES	3
THE CONTROL CHARTS	6
SPECIAL AID TABLES	11
PROPERTIES OF THE CHARTS	13
AN APPLICATION	15
REFERENCES	18

LIST OF TABLES AND FIGURES

TABLE 1. Special aid tables related to p-dimensional Student's distributions having ν degrees of freedom and the common correlation parameter ρ .

TABLE 2. Selected values of $t_{\alpha}(p, v, \rho)$ from reference [5].

TABLE 3. Selected values of $F_{\alpha}(p, v, \rho)$ from references [1] and [6].

TABLE 4. Estimated coefficients for the model (6.1) and values $\{v_{ii}\}$ from the diagonal of $V = (X'X)^{-1}$.

TABLE 5. Analysis of variance of the data in reference [12].

FIGURE 1a. A typical Shewhart control chart with warning line W_α , upper control limit C_α , and values warning at time 6 and signaling at time 7.

FIGURE 1b. A typical Shewhart control chart for plotting a statistic $\hat{\theta}$ with target value θ , lower ($W_{L\alpha}$) and upper ($W_{U\alpha}$) warning lines, and lower ($C_{L\alpha}$) and upper ($C_{U\alpha}$) control limits.

Accession For	
NTIS GRA&I	<input checked="" type="checkbox"/>
DTIC TAB	<input type="checkbox"/>
Unannounced	<input type="checkbox"/>
Justification	
Date:	
Pages:	
Covers	
Major	
Pile	Special

MONITORING AN INPUT-OUTPUT MODEL FOR
PRODUCTION. I. THE CONTROL CHARTS

D. R. Jensen, Y. V. Hui and P. M. Ghare

Virginia Polytechnic Institute
and State University

0. Abstract. Shewhart type control charts are ^{used} ~~given~~ for monitoring an input-output model against changes in form, against changes in its coefficients, and against changes in process variability. When a process is not in control due to changes in some coefficients, monitoring shifts to a diagnostic mode to identify the altered coefficients and thus the needed adjustments to production. Control limits from special aid tables are used; these are considered along with the choice of design. Operating characteristics of the charts are summarized under standard assumptions.

Acknowledgment. Partial support was provided by the U. S. Army Research Office through Grant No. DAAG-29-78-G-0172.

AMS 1980 subject classification. Primary 90B30.

Key words and phrases. Shewhart control charts, monitoring a model, monitoring the coefficients, diagnostic procedures, optimal operating conditions.

1. Introduction. Shewhart control charts are used routinely in monitoring the means and variances of quality characteristics in industrial production. These charts are easily maintained and interpreted and their operating characteristics are known. Other aspects of production are important in addition to the outgoing quality, yet little has been done towards monitoring them. This study deals specifically with the conversion of resources into units of product and with efficient resource use.

Production processes often may be formulated as input-output models of the type

$$y = \beta_0 + \beta_1 X_1 + \dots + \beta_p X_p + \epsilon \quad (1.1)$$

where y is the quantity produced; ϵ is a random error; $\{X_1, \dots, X_p\}$ are the levels of inputs such as the number of machine hours used (X_1), the quantity of raw materials converted (X_2), and the number of man-hours of labor required (X_3); and $\{\beta_1, \dots, \beta_p\}$ are rates of conversion of input to output such as machine productivity in units per hour (β_1), materials conversion in units of output per unit of raw materials used (β_2), and labor productivity in units per man-hour (β_3). The variables $\{X_1, \dots, X_p\}$ frequently include levels of inputs and functions of these levels as in second-order response models.

In practice an input-output model often is established in a small-scale pilot plant or in a regular production facility under careful scrutiny by process engineers. Such model may or may not apply after the process has gone on line or has seen extensive use. Response surface methodology and evolutionary operation are concerned with finding levels

of the input variables to achieve the most efficient use of resources. In order that operating conditions thus determined remain optimal, it is presumed that both the form of the model and the values of its coefficients remain stationary through time. Both, however, may change. The form of the model may change to include variables earlier held constant or to reflect changes in the type of dependence on inputs; values of the coefficients may change due to wear in machines or declining worker morale, for example. In practice it may be possible to adjust the process to its original state by replacing worn parts or by improving labor relations in the examples cited. Or, if the model has changed irrevocably, it may be necessary to establish revised operating conditions taking into account the altered form.

The object here is to monitor a model against changes in form, against changes in its coefficients, and against changes in process variability. The study is arranged in two parts. Part I gives charts for monitoring these changes, and it supplies the basic properties of these charts under standard assumptions. Related topics as developed in Part II include (i) properties of the charts when the usual assumptions fail, (ii) the notion of drifting processes, and (iii) stochastic bounds for certain distributions under drifting. Special features are that different charts may be maintained on different schedules as needed and, in monitoring the coefficients, that a diagnostic mode is available to aid in identifying the altered coefficients. Various modifications of the basic procedures are given to allow for flexibility in their use.

2. Preliminaries. Consider an expanded model of the type

$$y = \alpha + \sum_{i=1}^p \beta_i X_i + \sum_{j=1}^q \gamma_j Z_j + \epsilon \quad (2.1)$$

where $\{X_1, \dots, X_p\}$ are variables appearing in the original model and $\{Z_1, \dots, Z_q\}$ are additional variables which may or may not be adjusted in determining operating conditions. This model encompasses several avenues as follows through which changes in the model (1.1) may occur.

One possibility is that $\{Z_1, \dots, Z_q\}$ are further functions of the original input factors not included in $\{X_1, \dots, X_p\}$; then (2.1) represents a structural change in the dependence of output on inputs. For example, (1.1) may be a second-order response function and (2.1) a function of third order. Operating conditions considered optimal often differ widely between two such models.

A second possibility arises when $\{Z_1, \dots, Z_q\}$ are functions only of factors extraneous to the initial modeling in that they either were unknown or essentially were held fixed. Examples are batch temperature, line voltage, and the percent impurities of materials from a supplier, all of which may fluctuate appreciably when a process goes on line. When $\{Z_1, \dots, Z_q\}$ are held fixed the models (1.1) and (2.1) are related through the expression

$$\beta_0 = \alpha + \sum_{j=1}^q \gamma_j Z_j. \quad (2.2)$$

While the level of output now depends on the values of extraneous variables, optimal levels of the original variables often do not under this version of the model (2.1).

As a third possibility combining the other two, $\{Z_1, \dots, Z_q\}$ may be determined by levels of the original input factors and the levels of factors extraneous to these. This allows for structural changes in the original model as well as dependence on extraneous variables. When some of

$\{Z_1, \dots, Z_q\}$ are functions of the levels of both types of factors, optimal levels of the original variables generally are altered even when $\{\beta_1, \dots, \beta_p\}$ remain constant over time.

To monitor the model, observations $\{y_1, \dots, y_n\}$ are generated on each sampling occasion at levels $\{X_1, \dots, X_n\}$ specified according to a particular design, where $X_i = [X_{i0}, X_{i1}, \dots, X_{ip}]$ and $X_{i0} \equiv 1$ for $i = 1, 2, \dots, n$. In standard form the observational versions of (1.1) and (2.1) are

$$\underline{y} = \underline{X}\underline{\beta} + \underline{\varepsilon} \quad (2.3)$$

and

$$\underline{y} = \underline{X}\underline{\beta} + \underline{Z}\underline{\gamma} + \underline{\varepsilon} \quad (2.4)$$

respectively, where $\underline{y} = [y_1, \dots, y_n]'$; \underline{X} is a design matrix of order $[n \times (p+1)]$ and rank $p+1$; $\underline{\beta} = [\beta_0, \beta_1, \dots, \beta_p]'$ with β_0 replacing α in expression (2.1); $\underline{Z} (n \times q)$ is a matrix consisting of levels of the additional variables, often unknown; $\underline{\gamma} = [\gamma_1, \dots, \gamma_q]'$; and $\underline{\varepsilon} = [\varepsilon_1, \dots, \varepsilon_n]'$ is a vector of errors, all mutually uncorrelated and having the same variance σ^2 . Here the primes denote transposition. Usually the same experimental design is repeated on successive occasions, often with a single point replicated to give the observations $\{y_1^*, \dots, y_m^*\}$ having the sample mean \bar{y}^* . On each sampling occasion we compute one or more of (i) the Gauss-Markov estimates $\hat{\underline{\beta}} = (\underline{X}'\underline{X})^{-1}\underline{X}'\underline{y}$ under the model (1.1); (ii) the residual sum of squares $R(\hat{\underline{\beta}}) = (\underline{y} - \underline{X}\hat{\underline{\beta}})'(\underline{y} - \underline{X}\hat{\underline{\beta}})$; and (iii) the sample variance $s^2 = [(y_1^* - \bar{y}^*)^2 + \dots + (y_m^* - \bar{y}^*)^2]/(m-1)$. The latter provides a reasonable estimate for σ^2 regardless of the underlying model. On occasion σ^2 is assumed to be known or, if stationary over time, to have been estimated using the sample variance s_0^2 from a start-up period based on v degrees of freedom.

The ensuing developments are based on the following standard assumptions.

- (i) Independent random outcomes are observed on successive sampling occasions.
- (ii) The errors $\{e_1, \dots, e_n\}$ are distributed normally.
- (iii) The control values $\{\beta_0^*, \beta_1^*, \dots, \beta_p^*, \sigma_0^2\}$ for parameters of the original model are known.

Accordingly, needed values from standard distributions are $F_\alpha(r, v)$, the $100(1-\alpha)$ percentile of the central F distribution having r and v degrees of freedom, and $\chi_\alpha^2(v)$, the $100(1-\alpha)$ percentile of the central chi-squared distribution having v degrees of freedom. Other special values are $t_\alpha(p, v, R)$, the upper percentile of the central p -dimensional Student's distribution having v degrees of freedom and the correlation matrix $R(p \times p)$ such that $P(t_1 \leq t_\alpha(p, v, R), \dots, t_p \leq t_\alpha(p, v, R)) = 1-\alpha$; and $F_\alpha(p, v, R)$, the two-sided version such that $P(t_1^2 \leq F_\alpha(p, v, R), \dots, t_p^2 \leq F_\alpha(p, v, R)) = 1-\alpha$. These distributions are discussed in reference [4], for example; special aid tables are cited in a later section.

3. The Control Charts. To monitor a process samples are taken on successive occasions and appropriate statistics are computed. A control chart of Shewhart's type consists of successive values of a statistic plotted against time as the horizontal scale. Alpha-level control limits are provided beyond which the chart signals that the process is not in control, with α the probability of exceeding the limits on each occasion when the process is in control. A typical chart with one-sided limit is depicted in Figure 1a; a two-sided version is shown in Figure 1b. In the sections following we consider monitoring an input-output model against changes of




FIGURE 1a. A typical Shewhart control chart with warning line W_α , upper control limit C_α , and values warning at time 6 and signaling at time 7.




FIGURE 1b. A typical Shewhart control chart for plotting a statistic $\hat{\theta}$ with target value θ , lower ($W_{L\alpha}$) and upper ($W_{U\alpha}$) warning lines, and lower ($C_{L\alpha}$) and upper ($C_{U\alpha}$) control limits.

the types mentioned. In particular, for each type of change we stipulate (i) the statistics to be plotted, (ii) the control limits appropriate, and (iii) the corrective action to be taken when a chart signals.

3.1 Monitoring the structure. The purpose is to monitor the model (1.1) against changes of the form (2.1). The basic procedure uses an F chart of the type shown in Figure 1a with an upper control limit.

THE CHART. Plot values of the statistic

$$F_1 = R(\hat{\beta}) / (n-p-1)s^2. \quad (3.1)$$

THE CONTROL LIMIT. The chart signals a change in structure whenever

$$F_1 > F_{\alpha}(n-p-1, m-1). \quad (3.2)$$

CORRECTIVE ACTION. Use residual analysis to identify changes in the form of the model and to isolate extraneous variables now pertinent. Determine whether these extraneous variables may be adjusted for efficiency. If necessary revise the model and determine revised operating conditions.

OPTIONAL PROCEDURES. If the process variance σ^2 is known the statistic $X_1^2 = R(\hat{\beta}) / \sigma^2$ may be plotted on a chi-squared chart similar to Figure 1a with $\chi_{\alpha}^2(n-p-1)$ as the upper control limit. If σ^2 is stationary over time but otherwise unknown, the statistic $F_1' = R(\hat{\beta}) / (n-p-1)s_0^2$ may be plotted on an F chart and $F_{\alpha}(n-p-1, v)$ used as a control limit, where s_0^2 is an initial estimate based on v degrees of freedom.

3.2 Monitoring the coefficients. The purpose is to monitor against general alternatives changes in the coefficients of the model (1.1) from their designated values $\beta^* = [\beta_0^*, \beta_1^*, \dots, \beta_p^*]'$. The basic procedure uses an F chart as in Figure 1a.

THE CHART. Plot values of the statistic

$$F_2 = S(\hat{\beta}, \hat{\beta}^*) / (p+1)s^2 \quad (3.3)$$

where $S(\hat{\beta}, \hat{\beta}^*) = (\hat{\beta} - \hat{\beta}^*)' \underline{X}' \underline{X} (\hat{\beta} - \hat{\beta}^*)$.

THE CONTROL LIMIT. The chart signals a change in some one or more coefficients whenever

$$F_2 > F_{\alpha}(p+1, m-1). \quad (3.4)$$

CORRECTIVE ACTION. Monitoring shifts to the diagnostic mode of Section 3.3 in order to identify the altered coefficients and thus the specific adjustments to be made to the process.

OPTIONAL PROCEDURES. Two types of options are considered.

(i) If σ^2 is known the statistic $X_2^2 = S(\hat{\beta}, \hat{\beta}^*) / \sigma^2$ may be plotted on a chi-squared chart and $\chi_{\alpha}^2(p+1)$ used as a control limit. If σ^2 is stationary over time, justifying use of an initial estimate s_0^2 having v degrees of freedom, the statistic $F_2' = S(\hat{\beta}, \hat{\beta}^*) / (p+1)s_0^2$ may be plotted on an F chart and $F_{\alpha}(p+1, v)$ used as a control limit.

(ii) Suppose some subset $\{X_{i_1}, \dots, X_{i_t}\}$ of the p variables $\{X_1, \dots, X_p\}$ may be adjusted in determining efficient operating conditions, and let $\xi = [\beta_{i_1}, \dots, \beta_{i_t}]'$ be the corresponding coefficients. Then it may be desired to determine whether designated operating conditions for these variables remain optimal, i.e., whether the coefficients ξ all achieve their designated values $\xi^* = [\beta_{i_1}^*, \dots, \beta_{i_t}^*]'$. This may be accomplished on plotting the statistic $F_2^* = S(\hat{\xi}, \hat{\xi}^*) / ts^2$ on an F chart using $F_{\alpha}(t, m-1)$ as a control limit, where now $S(\hat{\xi}, \hat{\xi}^*) = (\hat{\xi} - \hat{\xi}^*)' \underline{M}^{-1} (\hat{\xi} - \hat{\xi}^*)$ and \underline{M} is the $(t \times t)$ matrix obtained from $(\underline{X}' \underline{X})^{-1}$ on deleting rows and columns not in the set $\{i_1, \dots, i_t\}$ and rearranging those remaining in the order (i_1, \dots, i_t) . In particular, when

optimal conditions depend on the levels of $\{X_1, \dots, X_p\}$ but not on the overall level of response, this gives a procedure for monitoring $\{\beta_1, \dots, \beta_p\}$ ignoring the value of β_0 .

3.3 The diagnostic mode. The purpose is to determine which coefficients have changed and thus the specific adjustments to be made to the process such as repairing machines or improving worker productivity. The basic procedure gives multipurpose use to a single control chart of the type shown in Figure 1a; other options are noted. Write $(\underline{X}'\underline{X})^{-1} = \underline{M} = [m_{ij}]$ with i and j ranging from 0 through p , and let $\underline{R} = [\rho_{ij}]$ be the correlation matrix for $\hat{\beta}$, which is determined by the choice of design.

THE CHART. Using different symbols plot the several statistics

$$t_i^2 = (\hat{\beta}_i - \beta_i^*)^2 / m_{ii} s^2, \quad i = 0, 1, \dots, p \quad (3.5)$$

on a single chart as in Figure 1a.

THE CONTROL LIMIT. The coefficient β_i is declared significantly different from its control value β_i^* whenever

$$t_i^2 > F_\alpha(p+1, m-1, \underline{R}) \quad (3.6)$$

for each $i = 0, 1, \dots, p$.

CORRECTIVE ACTION. Adjustments of the appropriate types are initiated for each coefficient found to differ significantly from its control value.

OPTIONAL PROCEDURES. Four options are considered.

(1) The estimate s^2 may be replaced by σ^2 if known or by s_0^2 from an initial period if variance is stationary. The corresponding changes in the control limit are to replace $m-1$ in $F_\alpha(p+1, m-1, \underline{R})$ by ∞ and v respectively for the two cases.

(ii) Separate charts may be maintained for the several coefficients as in Figure 1b. Here the target value is β_i^* for the i th chart, and the upper and lower control limits are given by $\beta_i^* \pm [m_{ii}s^2 F_\alpha(p+1, m-1, R)]^{1/2}$. This has the advantages that $\hat{\beta}_i$ may be plotted on its natural scale rather than the standardized scale of the single chart, and that trends above as well as below the control value may be followed. The disadvantage is that several charts are required.

(iii) Because the F chart of Section 3.2 monitors against general alternatives, it is appropriate that the diagnostic mode be carried out against two-sided alternatives. However, if one-sided alternatives are mandated throughout, then monitoring as in Section 3.2 may be omitted in favor of the following procedure. To monitor against one-sided upper alternatives, use different symbols to plot the statistics

$$t_i = (\hat{\beta}_i - \beta_i^*) / (m_{ii}s^2)^{1/2}; i = 0, 1, \dots, p \quad (3.7)$$

on a single chart as in Figure 1a with $t_\alpha(p+1, m-1, R)$ as the upper control limit. Alternatively, a separate chart may be maintained for each coefficient in which $\hat{\beta}_i$ is plotted on its natural scale with $\beta_i^* + (m_{ii}s^2)^{1/2} t_\alpha(p+1, m-1, R)$ as an upper control limit. Against one-sided lower alternatives the foregoing procedures may be followed using $-t_\alpha(p+1, m-1, R)$ and $\beta_i^* - (m_{ii}s^2)^{1/2} t_\alpha(p+1, m-1, R)$ respectively as lower control limits.

(iv) The foregoing procedures including options all may be adapted for monitoring a subset $\xi = [\beta_{i_1}, \dots, \beta_{i_t}]'$ of the parameters against their control values $\xi^* = [\beta_{i_1}^*, \dots, \beta_{i_t}^*]'$. The essential changes are to replace $p+1$ by t and M by the $(t \times t)$ matrix obtained on deleting rows and columns of $(X'X)^{-1}$ not in the set $\{i_1, \dots, i_t\}$ and rearranging those remaining in the order (i_1, \dots, i_t) .

3.4 Monitoring the process variance. The purpose is to determine whether the process variance σ^2 is maintained at its control value σ_0^2 .

Adjustment is initiated on evidence that σ^2 exceeds σ_0^2 .

THE CHART. Plot the statistic

$$X_3^2 = (m-1)s^2/\sigma_0^2 \quad (3.8)$$

on a chi-squared chart of the type shown in Figure 1a.

THE CONTROL LIMIT. The variance of the process is inferred to be excessive whenever

$$X_3^2 > \chi_\alpha^2(m-1). \quad (3.9)$$

CORRECTIVE ACTION. Adjustments to reduce the process variability are undertaken when the chart signals.

OPTIONAL PROCEDURES. Often the control variance σ_0^2 is not assumed known, but instead an estimate s_0^2 based on ν degrees of freedom is used from an initial period when the process is known to be in control. Then the statistic $F_3 = s^2/s_0^2$ is plotted on an F chart as in Figure 1a with $F_\alpha(m-1, \nu)$ as a control limit.

4. Special Aid Tables. Standard tables are widely available for use with the F and chi-squared charts irrespective of the particular experimental design. The same control limit applies on successive occasions as long as n is held fixed, whether or not the designs are all identical.

Owing to an excess of parameters, tables of percentiles associated with multidimensional Student's distributions are available only for the equicorrelated case in which $\rho_{ij} = \rho$ for all $i \neq j$. A summary of these sources is given in the accompanying Table 1 together with ranges for the

TABLE 1. Special aid tables related to p-dimensional Student's distributions having ν degrees of freedom and the common correlation parameter ρ .

Percentiles Tabulated	Range of Values				Reference
	α	p	ν	ρ	
$t_{\alpha}(p, \nu, \rho)$	*	1(1)10	5(1)35	0(0.1)0.9	[5]
$t_{\alpha}(p, \nu, \rho)$	* *	1(1)10	5(1)35	0(0.1)0.9	[7]
$F_{\alpha}(p, \nu, 0)$	*	1(1)12	5(1)45	0	[1]
$F_{\alpha}(p, \nu, \rho)$	*	1(1)10	5(1)35	0.1(0.1)0.9	[6]

* $\alpha = 0.01, 0.025, 0.05, 0.10$

* * $\alpha = 0.01, 0.05$

several parameters in question. Here $t_{\alpha}(p, v, \rho)$ and $F_{\alpha}(p, v, \rho)$ are upper percentiles of the equicorrelated distributions having the correlation parameter ρ ; these correspond respectively to $t_{\alpha}(p, v, R)$ and $F_{\alpha}(p, v, R)$ in the general case. In addition, tables of $1-\alpha = P(t_1 \leq a, t_2 \leq a)$ are given in reference [8], and values of $1-\alpha = P(|t_1| \leq a, |t_2| \leq a)$ in reference [9], in the bivariate case for the values $a = 1.0(0.1)5.5$, $v = 5(1)35$, and $|\rho| = 0(0.1)0.9$. Tables of $1-\alpha = P(|t_1| \leq a, \dots, |t_p| \leq a)$ are given in reference [2] for $a = 0.2(0.2)6.0$; $v = 4(2)12(4)24, 30, \infty$; $p = 2(2)20$; and $\rho = 0(0.1)0.9$ and $\rho = -1/(p-1)$, all based on Monte Carlo methods. Abbreviated tables of $t_{\alpha}(p, v, \rho)$ and $F_{\alpha}(p, v, \rho)$ appear in Tables 2 and 3 as taken from the sources cited in Table 1. Values of $t_{\alpha}(p, v, 0)$ and $F_{\alpha}(p, v, 0)$ assume a special role for reasons to be given.

On occasion the design matrix \underline{X} may be chosen arbitrarily. In order that the same control limits apply in the diagnostic mode, it is necessary that successive designs have the same correlation parameters. To expedite the diagnostic mode it is recommended whenever possible that \underline{X} be chosen such that $\rho_{ij} = \rho$ for all $i \neq j$, for then the special aid tables apply directly. For this it suffices that $(\underline{X}'\underline{X})^{-1} = \underline{D} + \rho \underline{a}\underline{a}'$ with \underline{D} diagonal and \underline{a} chosen suitably or, equivalently, that $(\underline{X}'\underline{X}) = \underline{D}^{-1} + \gamma \underline{b}\underline{b}'$ have the same structure (cf. reference [3], page 170). In particular, an orthogonal design yields $\rho_{ij} = 0$ for all $i \neq j$, in which case tables of $t_{\alpha}(p, v, 0)$ and $F_{\alpha}(p, v, 0)$ are appropriate. Unfortunately, equicorrelated designs are not possible in many cases such as second order response models. However, by using appropriate probability inequalities the tabulated percentiles often may be applied conservatively to more general correlation structures.

For one-sided Gaussian limits Slepian (1962) has shown that the probability $P_R(Z_1 \leq a_1, \dots, Z_p \leq a_p)$ is an increasing function of each ρ_{ij} .

TABLE 2. Selected values of $t_{\alpha}(p, v, \rho)$ from reference [5].

v	p	$\rho = 0$			$\rho = 0.4$			$\rho = 0.8$		
		2	4	6	2	4	6	2	4	6
$\alpha = 0.05$										
6		2.42	2.89	3.17	2.36	2.76	2.99	2.22	2.48	2.61
8		2.28	2.70	2.95	2.24	2.60	2.80	2.12	2.35	2.47
10		2.21	2.60	2.82	2.17	2.50	2.69	2.06	2.27	2.39
15		2.12	2.47	2.66	2.08	2.39	2.56	1.98	2.18	2.29
20		2.08	2.40	2.59	2.04	2.33	2.50	1.95	2.14	2.25
25		2.05	2.37	2.55	2.02	2.30	2.46	1.92	2.12	2.22
30		2.03	2.34	2.52	2.00	2.28	2.44	1.91	2.10	2.20
$\alpha = 0.01$										
6		3.68	4.25	4.59	3.63	4.12	4.40	3.48	3.80	3.97
8		3.34	3.80	4.07	3.30	3.71	3.94	3.19	3.45	3.60
10		3.16	3.56	3.79	3.13	3.49	3.69	3.03	3.27	3.40
15		2.94	3.28	3.47	2.92	3.22	3.40	2.83	3.05	3.16
20		2.84	3.14	3.32	2.82	3.10	3.26	2.75	2.94	3.05
25		2.78	3.07	3.24	2.77	3.03	3.18	2.70	2.89	2.99
30		2.75	3.02	3.18	2.73	2.99	3.14	2.66	2.85	2.95

TABLE 3. Selected values of $F_{\alpha}(p, v, \rho)$ from references [1] and [6].

v	p	$\rho = 0$			$\rho = 0.4$			$\rho = 0.8$		
		2	4	6	2	4	6	2	4	6
$\alpha = 0.05$										
6		8.50	11.48	13.43	8.31	10.95	12.61	7.56	9.16	10.09
8		7.39	9.78	11.32	7.24	9.37	10.70	6.63	7.95	8.71
10		6.81	8.90	10.24	6.68	8.55	9.72	6.15	7.33	8.00
15		6.12	7.87	8.96	6.02	7.60	8.56	5.58	6.59	7.17
20		5.81	7.41	8.40	5.72	7.17	8.05	5.32	6.26	6.80
25		5.64	7.14	8.07	5.55	6.93	7.76	5.17	6.07	6.58
30		5.52	6.98	7.87	5.44	6.77	7.57	5.07	5.95	6.45
$\alpha = 0.01$										
6		18.24	23.58	27.07	17.94	22.70	25.72	16.67	19.63	21.35
8		14.51	18.26	20.68	14.31	17.70	19.82	13.44	15.61	16.87
10		12.72	15.75	17.68	12.57	15.33	17.05	11.87	13.69	14.73
15		10.75	13.02	14.44	10.65	12.75	14.04	10.14	11.57	12.39
20		9.92	11.87	13.08	9.83	11.67	12.78	9.40	10.67	11.39
25		9.45	11.25	12.35	9.38	11.07	12.09	8.99	10.17	10.85
30		9.16	10.85	11.89	9.10	10.70	11.66	8.73	9.86	10.50

where $\underline{Z} = [Z_1, \dots, Z_p]'$ is a p -dimensional standard Gaussian vector having the correlation matrix $R = [\rho_{ij}]$. Applying Slepian's result conditionally on s^2 and noting that inequalities are preserved on averaging over the conditioning variable, we have the following useful result. Let $\rho^* = \min\{\rho_{ij}; i \neq j\}$; then the inequality

$$P(t_1 \leq t_\alpha(p, v, \rho^*), \dots, t_p \leq t_\alpha(p, v, \rho^*)) \geq 1 - \alpha \quad (4.1)$$

holds uniformly for all nonsingular correlation matrices R having $\rho^* = \min\{\rho_{ij}; i \neq j\}$, with equality when $\rho_{ij} = \rho^*$ for all $i \neq j$. Through this mechanism special aid tables now available can be applied conservatively for any design matrix X in the sense that the actual operating level is no greater than α .

For two-sided limits a result of Šidák (1967) applies directly to give

$$P(t_1^2 \leq F_\alpha(p, v, 0), \dots, t_p^2 \leq F_\alpha(p, v, 0)) \geq 1 - \alpha \quad (4.2)$$

uniformly for every correlation matrix R , with equality when $\rho_{ij} = 0$ for all $i \neq j$ as in the case of orthogonal designs. Tables of $F_\alpha(p, v, 0)$ as given in reference [1] thus apply conservatively in the case of two-sided limits for every choice of design.

5. Properties of the Charts. We examine performance characteristics of the charts under standard assumptions as set forth in Section 2. The run length of a chart is the number of successive samples taken before the chart signals that the process is not in control. For many purposes the operating characteristics of a chart may be summarized succinctly in terms of the distribution of its run lengths. We follow this approach here.

Consider first those F and chi-squared charts of the preceding sections not using s_0^2 , and suppose the parameters monitored remain fixed through time. Then by independence and the identical distributions of successive statistics associated with each chart, it follows that its run-length distribution is geometric with parameter γ equal to the probability of exceeding the control limit on each occasion. A consequence is that each chart eventually signals with unit probability. Moreover, because for each chart the normal-theory tests have power increasing monotonically with departures from control, and because geometric distributions are stochastically decreasing in the parameter γ , it follows that the run lengths become stochastically smaller, and thus each chart tends to signal more frequently, with increasing departures from control.

Modifications to the basic charts were given using an estimate s_0^2 from an initial period. The resulting run-length distributions are complicated, being no longer geometric owing to dependence among the successive statistics. Moreover, even under independence the geometric property fails when the parameters monitored are not constant through time. Properties of the actual run-length distributions resulting from failure of these and other assumptions are considered in detail in Part II of this study.

Similar assessments may be given for the diagnostic charts. Here it is useful to define the run length as the number of sampling occasions in which no chart signals and thus no diagnoses are rendered. For example, the run-length distribution is geometric with parameter α when the process is in control and exact tables are used. If instead approximate procedures are used based on (4.1) or (4.2), then the actual run length is stochastically larger than one having the geometric distribution with parameter α , which thus provides a bound.

6. An Application. Taraman and Lambert [12] reported a study on conditions for machining steel in which the logarithm (y) of tool life in minutes was regressed on coded variables x_1 , x_2 , and x_3 representing logarithms of cutting speed, rate of feed, and depth of cut, respectively. A partially replicated central composite design was used. A second-order model of the type

$$y = \beta_0 + \beta_1 x_1 + \beta_2 x_2 + \beta_3 x_3 + \beta_{11} x_1^2 + \beta_{22} x_2^2 + \beta_{33} x_3^2 + \epsilon \quad (6.1)$$

having only linear and quadratic terms in each variable was established provisionally. We treat this data set as one from a succession of experiments to be used for monitoring tool life in production. Taraman and Lambert [12] used the shapes of this and two related response surfaces in determining operating conditions. The shape of response thus is to be monitored in addition to adequacy of the model and its residual variance. As the shape of a second-order response surface is determined apart from centering by its second-order coefficients, we monitor the latter using one of the optional procedures of Section 3.2.

The design is central composite, built around a single replication of a 2^3 factorial experiment with vertices at ± 1 for the coded variables. The center point was replicated four times, and two replications were made at each of the coded values $\pm\sqrt{2}$ on the three coordinate axes. Estimates for parameters of the model (6.1) are given in Table 4 along with the values v_{ii} from the diagonal of $V = (X'X)^{-1}$. The analysis of variance is summarized in Table 5, the pure error component giving the estimate $s^2 = 0.009275$ for σ^2 having 9 degrees of freedom.

To monitor for changes in the structure of the model (6.1) we compute the statistic $F_1 = 0.023171/0.009275 = 2.498$ as in Section 3.1. The upper control limit at the level $\alpha = 0.05$ is $F_{0.05}(8,9) = 3.23$, supporting the conclusion that the form of the model is as specified.

TABLE 4. Estimated coefficients for the model (6.1)
and values $\{v_{ii}\}$ from the diagonal of $\underline{V} = (\underline{X}'\underline{X})^{-1}$.

Parameter	Estimate	v_{ii}
β_0	3.500933	0.208330
β_1	-0.303106	0.062501
β_2	-0.092222	0.062501
β_3	-0.091540	0.062501
β_{11}	0.048230	0.083335
β_{22}	0.041642	0.083335
β_{33}	0.068205	0.083335

TABLE 5. Analysis of variance of the data in reference [12].

Source	Degrees of Freedom	Sum of Squares	Mean Square
Model	6	1.812867	0.302144
Lack of Fit	8	0.185366	0.023171
Error	9	0.083479	0.009275

In order to monitor the shape coefficients, we suppose that their target values from a base line period are $\xi^* = (\beta_{11}^*, \beta_{22}^*, \beta_{33}^*)' = (0.13, 0.09, 0.03)'$. From the matrix $(X'X)^{-1}$ we extract the lower principal diagonal block of order (3×3) to get

$$\underline{M} = \begin{bmatrix} 0.083335 & 0.020833 & 0.020833 \\ 0.020833 & 0.083335 & 0.020833 \\ 0.020833 & 0.020833 & 0.083335 \end{bmatrix} \quad (6.2)$$

using the notation of Section 3.2 under option (ii). On evaluating $S(\hat{\xi}, \xi^*)$ as the quadratic form

$$(\hat{\xi} - \xi^*)' \underline{M}^{-1} (\hat{\xi} - \xi^*) = 0.119455 \quad (6.3)$$

we compute $F_2^* = S(\hat{\xi}, \xi^*)/3s^2 = 4.293$. As the upper control limit at the level $\alpha = 0.05$ is $F_{0.05}(3,9) = 3.86$, the chart signals a shift in one or more shape coefficients from their target values. Monitoring now shifts to the diagnostic mode of Section 3.3 to identify which coefficients may have changed.

Proceeding as in Section 3.3 we compute the Studentized statistics $t_1^2 = (\hat{\beta}_{11} - \beta_{11}^*)^2/m_{11}s^2 = 8.651$, $t_2^2 = (\hat{\beta}_{22} - \beta_{22}^*)^2/m_{22}s^2 = 3.025$, and $t_3^2 = (\hat{\beta}_{33} - \beta_{33}^*)^2/m_{33}s^2 = 1.888$, where from (6.2) $m_{11} = m_{22} = m_{33} = 0.083335$. It is clear from the form of \underline{M} that $(\hat{\beta}_{11}, \hat{\beta}_{22}, \hat{\beta}_{33})$ are equicorrelated having the common correlation $\rho = 0.25$. The upper control limit required for the diagnostic chart thus is $F_\alpha(p, v, \rho)$ in the notation of Section 4 with $p = 3$, $v = 9$ and $\rho = 0.25$. Interpolating linearly between $F_{0.05}(3,9,0.2) = 8.26$ and $F_{0.05}(3,9,0.3) = 8.18$ using the tables in [6], we obtain the required critical value $F_{0.05}(3,9,0.25) = 8.22$. As t_1^2 exceeds this value and t_2^2 and t_3^2 do not, we infer that the second-order coefficient for cutting speed is significantly smaller than its target value. Thus either an adjustment to the process should be made, or operating conditions should be modified to reflect the altered coefficient.

If the process variance is to be monitored against the control value $\sigma_0^2 = 0.01$, we find that $X_3^2 = 9s^2/\sigma_0^2 = 8.348$. The upper control limit is $\chi_\alpha^2(v) = 16.919$ with $\alpha = 0.05$ and $v = 9$, indicating that the process variance remains in control.

REFERENCES

- [1] Armitage, J.V. and Krishnaiah, P.R. (1964). "Tables for the Studentized largest chi-square distribution and their applications." *Report ARL64-188*, Aerospace Research Laboratories, Dayton, OH.
- [2] Dunn, O.J., Kronmal, R.A. and Yee, W.J. (1968). "Tables of the multivariate t distribution." *Report*, School of Public Health, UCLA, Los Angeles, CA.
- [3] Graybill, F.A. (1969). *Introduction to Matrices with Applications in Statistics*. Wadsworth Publishing Co., Belmont, CA.
- [4] Johnson, N.L. and Kotz, S. (1972). *Distributions in Statistics: Continuous Multivariate Distributions*. John Wiley and Sons, New York.
- [5] Krishnaiah, P.R. and Armitage, J.V. (1965). "Percentage points of the multivariate t distribution." *Report ARL65-199*, Aerospace Research Laboratories, Dayton, OH.
- [6] Krishnaiah, P.R. and Armitage, J.V. (1965). "Probability integrals of the multivariate F distribution, with tables and applications." *Report ARL65-236*, Aerospace Research Laboratories, Dayton, OH.
- [7] Krishnaiah, P.R. and Armitage, J.V. (1966). "Tables for multivariate t distribution." *Sankhyā* 28B: 31-56.
- [8] Krishnaiah, P.R., Armitage, J.V. and Breiter, M.C. (1969). "Tables for the probability integrals of the bivariate t distribution." *Report ARL69-0060*, Aerospace Research Laboratories, Dayton, OH.

- [9] Krishnaiah, P.R., Armitage, J.V. and Breiter, M.C. (1969). "Tables for the bivariate t distribution." *Report ARL69-0210*, Aerospace Research Laboratories, Dayton, OH.
- [10] Šidák, Z. (1967). "Rectangular confidence regions for the means of multivariate normal distributions." *J. Amer. Statist. Assoc.* 62: 626-633.
- [11] Slepian, D. (1962). "The one-sided barrier problem for Gaussian noise." *Bell System Tech. J.* 41: 463-501.
- [12] Taraman, K. S. and Lambert, B. K. (1972). "Application of response surface methodology to the selection of machining variables." *AIIE Trans.* 4: 111-115.

REPORT DOCUMENTATION PAGE		READ INSTRUCTIONS BEFORE COMPLETING FORM
1. REPORT NUMBER Q-6	2. GOVT ACCESSION NO.	3. RECIPIENT'S CATALOG NUMBER
4. TITLE (and Subtitle) MONITORING AN INPUT-OUTPUT MODEL FOR PRODUCTION. I. THE CONTROL CHARTS		5. TYPE OF REPORT & PERIOD COVERED Technical Report
		6. PERFORMING ORG. REPORT NUMBER Q-6
7. AUTHOR(s) D. R. Jensen, Y. V. Hui, and P. M. Ghare		8. CONTRACT OR GRANT NUMBER(s) DAAG-29-78-G-0172
9. PERFORMING ORGANIZATION NAME AND ADDRESS Virginia Polytechnic Institute Blacksburg, Virginia 24061		10. PROGRAM ELEMENT, PROJECT, TASK AREA & WORK UNIT NUMBERS
11. CONTROLLING OFFICE NAME AND ADDRESS U. S. Army Research Office Post Office Box 12211 Research Triangle Park, NC 27709		12. REPORT DATE December 1980
		13. NUMBER OF PAGES 27
14. MONITORING AGENCY NAME & ADDRESS (if different from Controlling Office)		15. SECURITY CLASS. (of this report) Unclassified
		15a. DECLASSIFICATION/DOWNGRADING SCHEDULE NA
16. DISTRIBUTION STATEMENT (of this Report) Approved for public release; distribution unlimited.		
17. DISTRIBUTION STATEMENT (of the abstract entered in Block 20, if different from Report) NA		
18. SUPPLEMENTARY NOTES The findings in this report are not to be construed as an official Department of the Army position, unless so designated by other authorized documents.		
19. KEY WORDS (Continue on reverse side if necessary and identify by block number) Shewhart control charts, monitoring a model, monitoring the coefficients, diagnostic procedures, optimal operating conditions.		
20. ABSTRACT (Continue on reverse side if necessary and identify by block number) Shewhart type control charts are given for monitoring an input-output model against changes in form, against changes in its coefficients, and against changes in process variability. When a process is not in control due to changes in some coefficients, monitoring shifts to a diagnostic mode to identify the altered coefficients and thus the needed adjustments to		

20.

production. Control limits from special aid tables are used; these are considered along with the choice of design. Operating characteristics of the charts are summarized under standard assumptions.